



BEAMZ
MADE
EAZY

155.109_155.113 V1.3

BTM100WW & BTM250WW

QUICK START GUIDE

CONTROL MENU

MENU			DESCRIPTION
DMX	Address	A000-A512	DMX address setting
	Control mode		2CH/3CH/5CH
STATIC	DIMMER	000-255	Strobe from slow to fast
	STROBE	000-255	
	ZOOM	000-255	
PERSONALITY	Dim Curve		Linear
			Square Law
			INV Square Law
			S-Curve
	Dim Speed		OFF
			Low
			Medium
			High
	Frequency		1000Hz
			1200Hz
			1500Hz
			2000Hz
			4000Hz
			8000Hz
			16000Hz
			24000Hz
	Fan Mode		Full
			Auto
			Silent
	DMX Hold		Hold/Blackout
INFO	Version		Ver:xx.xx
	RDM UID	UID:	
	Usage Time		Power On
			LED Total
	Temperature		Celsius
			Fahrenheit
	Fan speed	RMP xxx	
RESET			Yes/No

DMX CHANNELS

2 CHANNELS

CHANNELS	FUNCTION	VALUE	DESCRIPTION
1	MASTER DIMMER	000-255	Master Dimmer 0-100%
2	ZOOM	000-255	Zoom 0-100%

3 CHANNELS

CHANNELS	FUNCTION	VALUE	DESCRIPTION
1	MASTER DIMMER	000-255	Master Dimmer 0-100%
2	ZOOM	000-255	Zoom 0-100%
3	STROBE	000-002	No function
		003-255	Strobe slow to fast

5 CHANNELS

CHANNELS	FUNCTION	VALUE	DESCRIPTION
1	MASTER DIMMER	000-255	Master Dimmer 0-100%
2	DIMMER FINE	000-255	Dimmer Fine
3	ZOOM	000-255	Zoom 0-100%
4	STROBE	000-002	No function
		003-255	Strobe slow to fast
5	DIMMER SPEED	000-030	Fade off
		031 - 060	Low
		061 - 090	Medium
		091 - 255	High



BEAMZ

YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT

 **beamZ^{Pro}**

offers a wide range of high performance lighting equipment and related accessories for the rental, entertainment and architectural lighting markets. BeamZ Pro stands for performance, innovation and value pricing!



BEAMZLIGHTING.COM