



BEAMZ
MADE
EAZY

151.802 V1.1

DOTBAR BAT1

QUICK START GUIDE

CONTROL MENU

If the display is in standby, unlock it:



MENU		DESCRIPTION	
SET UP	Dimmer All	000-255	Master dimmer
	White Balance	Red	000-255
		Green	000-255
		Blue	000-255
		White	000-255
	Remote	On	
		Off	
	Dimmer Speed	Speed 1	
		Speed 2	
		Speed 3	
		Speed 4	
		Speed 5	
	Key lock	Off	Activate key lock yes/no
		On	
	Display	30S	Display sleep mode or on
		On	
	Max Temp	Choose between 30 -65	Choose max temp
INFORMATION	Software Ver		Shows software version
	RDM UID		Shows RDM address
	Working time	*****H**M	Shows Working hours
	Hardware Ver		Shows hardware version
FACTORY RESET		+/-/+/-/Enter	Reset mode
DMX MODE	Address	001-512	Select a DMX Channel
	Channel	3CH,08CH,12CH,32CH,37CH	Select a Channel mode
DIMMER CURVE		Linear,Square Law,Inv.Squ.Law,S-Curve	Select a Dimcurve
DMX STATE		Hold/ Blackout	Select what to do when there is no DMX signal input.
SLAVE MODE		Slave/ Master	Select Slave/ Master mode
AUTO MODE	Speed	001-030	Select speed auto mode
	Auto	001-013	Select different auto mode
STATIC COLOR	Red	000-255	Adjust dimming
	Green	000-255	
	Blue	000-255	
	White	000-255	Adjust Color
	Color	000-062	
	Strobe	000-020	
CCT		2700/3200/3500/4000/5000/5600/ 6000/6500/7000/7500K/8000K	

DMX CHANNELS

3 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	HUE	000-255	Hue
2	SATURATION	000-255	Saturation
3	VALUE	000-255	Value

8 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	DIMMER	000- 255	Dimmer
2	DIMMER CURVE	000-063	Linear
		064-127	Square Law
		128-191	Inv.Squ.Law
		192-255	S-Curve
3	DIMMER SPEED	000-005	No Function
		006-049	Dimmer Speed1
		050-099	Dimmer Speed2
		100-149	Dimmer Speed3
		150-199	Dimmer Speed4
		200-255	Dimmer Speed5
4	RED	000-255	Red
5	GREEN	000-255	Green
6	BLUE	000-255	Blue
7	WHITE	000-255	White
8	STROBE	000-009	No Function
		010-019	Strobe1
		020-029	Strobe2
		030-039	Strobe3
		040-049	Strobe4
		050-059	Strobe5
		060-069	Strobe6
		070-079	Strobe7
		080-089	Strobe8
		090-099	Strobe9
		100-109	Strobe10
		110-119	Strobe11
		120-129	Strobe12
		130-139	Strobe13
		140-149	Strobe14
		150-159	Strobe15
		160-169	Strobe16
		170-179	Strobe17
		180-189	Strobe18
		190-199	Strobe19
		200-255	Strobe20

12 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	DIMMER	000-255	Dimmer
2	DIMMER CURVE	001-063	Linear
		064-127	Square Law
		128-191	Inv.Squ.Law
		192-255	S-Curve
3	DIMMER SPEED	000-005	No Function
		006-049	Dimmer Speed1
		050-099	Dimmer Speed2
		100-149	Dimmer Speed3
		150-199	Dimmer Speed4
		200-255	Dimmer Speed5
4	RED	000-255	Red
5	GREEN	000-255	Green
6	BLUE	000-255	Blue
7	WHITE	000-255	White
8	STROBE	000-009	No Function
		010-019	Strobe1
		020-029	Strobe2
		030-039	Strobe3
		040-049	Strobe4
		050-059	Strobe5
		060-069	Strobe6
		070-079	Strobe7
		080-089	Strobe8
		090-099	Strobe9
		100-109	Strobe10
		110-119	Strobe11
		120-129	Strobe12
		130-139	Strobe13
		140-149	Strobe14
		150-159	Strobe15
		160-169	Strobe16
		170-179	Strobe17
		180-189	Strobe18
		190-199	Strobe19
9	COLOR	200-255	Strobe20
		000-007	No Function
		008-011	Color1
		012-015	Color2
		016-019	Color3
		020-023	Color4
		024-027	Color5
		028-031	Color6
		032-035	Color7
		036-039	Color8
		040-043	Color9
		044-047	Color10
		048-051	Color11
		052-055	Color12
		056-059	Color13

			060-063	Color14
			064-067	Color15
			068-071	Color16
			072-075	Color17
			076-079	Color18
			080-083	Color19
			084-087	Color20
			088-091	Color21
			092-095	Color22
			096-099	Color23
			100-103	Color24
			104-107	Color25
			108-111	Color26
			112-115	Color27
			116-119	Color28
			120-123	Color29
			124-127	Color30
			128-131	Color31
			132-135	Color32
			136-139	Color33
			140-143	Color34
			144-147	Color35
			148-151	Color36
			152-155	Color37
			156-159	Color38
			160-163	Color39
			164-167	Color40
			168-171	Color41
			172-175	Color42
			176-179	Color43
			180-183	Color44
			184-187	Color45
			188-191	Color46
			192-195	Color47
			196-199	Color48
			200-203	Color49
			204-207	Color50
			208-211	Color51
			212-215	Color52
			216-219	Color53
			220-223	Color54
			224-227	Color55
			228-231	Color56
			232-235	Color57
			236-239	Color58
			240-243	Color59
			244-247	Color60
			248-251	Color61
			252-255	Color62
10	CCT	000-015	No Function	
		016-035	2000K	
		036-055	3200K	

		056-075	3500K
		076-095	4000K
		096-115	4500K
		116-135	5000K
		136-155	5600K
		156-175	6000K
		176-195	6500K
		196-215	7000K
		216-235	7500K
		236-255	8000K
		000-007	No Function
		008-027	Auto1
11	AUTO	028-047	Auto2
		048-067	Auto3
		068-087	Auto4
		088-107	Auto5
		108-127	Auto6
		128-147	Auto7
		148-167	Auto8
		168-187	Auto9
		188-207	Auto10
		208-227	Auto11
		228-247	Auto12
		248-255	Auto13
12	AUTO SPEED	000-255	Auto Speed (slow -fast)

32 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	RED1-2	000- 255	Red1-2
2	GREEN1-2	000-255	Green1-2
3	BLUE1-2	000-255	Blue1-2
4	WHITE1-2	000-255	White1-2
5	RED 3-4	000-255	Red 3-4
6	GREEN3-4	000-255	Green3-4
7	BLUE3-4	000-255	Blue3-4
8	WHITE3-4	000-255	White3-4
9	RED 5-6	000-255	Red 5-6
10	GREEN5-6	000-255	Green5-6
11	BLUE5-6	000-255	Blue5-6
12	WHITE5-6	000-255	White5-6
13	RED 7-8	000-255	Red 7-8
14	GREEN7-8	000-255	Green7-8
15	BLUE7-8	000-255	Blue7-8
16	WHITE7-8	000-255	White7-8
17	RED 9-10	000-255	Red 9-10
18	GREEN9-10	000-255	Green9-10
19	BLUE9-10	000-255	Blue9-10
20	WHITE9-10	000-255	White9-10
21	RED 11-12	000-255	Red 11-12
22	GREEN11-12	000-255	Green11-12
23	BLUE11-12	000-255	Blue11-12
24	WHITE11-12	000-255	White11-12

25	RED 13-14	000-255	Red 13-14
26	GREEN13-14	000-255	Green13-14
27	BLUE13-14	000-255	Blue13-14
28	WHITE13-14	000-255	White13-14
29	RED 15-16	000-255	Red 15-16
30	GREEN15-16	000-255	Green15-16
31	BLUE15-16	000-255	Blue15-16
32	WHITE15-16	000-255	White15-16

37 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	DIMMER	000- 255	Dimmer
		000-063	Linear
		064-127	Square Law
2	DIMMER CURVE	128-191	Inv.Squ.Law
		192-255	S-Curve
		000-005	No Function
		006-049	Dimmer Speed1
3	DIMMER SPEED	050-099	Dimmer Speed2
		100-149	Dimmer Speed3
		150-199	Dimmer Speed4
		200-255	Dimmer Speed5
		000-007	No Function
		008-027	Auto1
		028-047	Auto2
		048-067	Auto3
		068-087	Auto4
		088-107	Auto5
4	AUTO	108-127	Auto6
		128-147	Auto7
		148-167	Auto8
		168-187	Auto9
		188-207	Auto10
		208-227	Auto11
		228-247	Auto12
		248-255	Auto13
5	AUTO SPEED	000-255	Auto Speed (slow -fast)
6	RED1-2	000- 255	Red1-2
7	GREEN1-2	000-255	Green1-2
8	BLUE1-2	000-255	Blue1-2
9	WHITE1-2	000-255	White1-2
10	RED 3-4	000- 255	Red 3-4
11	GREEN3-4	000-255	Green3-4
12	BLUE3-4	000-255	Blue3-4
13	WHITE3-4	000-255	White3-4
14	RED 5-6	000- 255	Red 5-6
15	GREEN5-6	000-255	Green5-6
16	BLUE5-6	000-255	Blue5-6
17	WHITE5-6	000-255	White5-6
18	RED 7-8	000- 255	Red 7-8
19	GREEN7-8	000-255	Green7-8
20	BLUE7-8	000-255	Blue7-8



21	WHITE7-8	000-255	White7-8
22	RED 9-10	000- 255	Red 9-10
23	GREEN9-10	000-255	Green9-10
24	BLUE9-10	000-255	Blue9-10
25	WHITE9-10	000-255	White9-10
26	RED 11-12	000- 255	Red 11-12
27	GREEN11-12	000-255	Green11-12
28	BLUE11-12	000-255	Blue11-12
29	WHITE11-12	000-255	White11-12
30	RED 13-14	000- 255	Red 13-14
31	GREEN13-14	000-255	Green13-14
32	BLUE13-14	000-255	Blue13-14
33	WHITE13-14	000-255	White13-14
34	RED 15-16	000- 255	Red 15-16
35	GREEN15-16	000-255	Green15-16
36	BLUE15-16	000-255	Blue15-16
37	WHITE15-16	000-255	White15-16









BEAMZ

YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT

 **beamZ^{Pro}**

offers a wide range of high performance lighting equipment and related accessories for the rental, entertainment and architectural lighting markets. BeamZ Pro stands for performance, innovation and value pricing!



BEAMZLIGHTING.COM